APPLICATION

FOR

UNITED STATES LETTERS PATENT

TITLE: I/Q IMBALANCE CORRECTION

APPLICANT: ERNEST T. TSUI AND JANE LIN

CERTIFICATE OF MAILING BY EXPRESS MAIL

Express Mail Label No. EL486016139US

I hereby certify under 37 CFR §1 10 that this correspondence is being deposited with the United States Postal Service as Express Mail Post Office to Addressee with sufficient postage on the date indicated below and is addressed to the Commissioner for Patents, Washington, D C 20231.

12/31/01
Date of Deposit

Signature

Leroy Jenkins

Typed or Printed Name of Person Signing Certificate

IQ IMBALANCE CORRECTION

FIELD OF INVENTION

This invention relates to wireless data transmission.

BACKGROUND

In a QAM ("quadrature amplitude modulation") data
transmission system, the in-phase ("I") and quadrature ("Q")
components of a signal identify a symbol being carried by
that signal. To transmit a desired symbol, the IQ components
corresponding to that symbol must be modulated onto a carrier
wave. In a direct modulation system, the IQ ratio is
modulated by controlling the amplitudes of two sinusoids
separated by ninety degrees in phase. When these two
sinusoids are combined, the resulting signal defines a point
(hereafter referred to as the "received point") in the IQ
plane.

A set of constellation points in the IQ plane defines
the set of symbols that can be transmitted. To the extent
that a received point fails to align perfectly with a
constellation point corresponding to the desired symbol, an
IQ imbalance error may have been introduced.

The extent to which such IQ imbalance errors can be
tolerated depends on the distribution of constellation
points. For example, in a QPSK system, there are only four

constellation points, one in each quadrant of the IQ plane.

As a result, so long as the IQ imbalance error leaves the

received point in the correct quadrant, there is no symbol

transmission error. However, in a modern 64-QAM system,

sixty-four constellation points crowd the IQ plane. As a

result, even a modest IQ imbalance error can easily place the

received point near the wrong constellation point. This

results in a symbol transmission error.

To increase data transmission speed, it is desirable to

send several symbols at the same time. This can be achieved

by concurrently transmitting each of several symbols onto

carriers having different frequencies. To avoid interference

between the carriers without consuming excessive bandwidth,

the carrier frequencies are selected such that the peak of

the spectrum of any one carrier coincides with nulls of the

spectra of all other carriers. This technique, referred to as

"orthogonal frequency division multiplexing" ("OFDM") enables

several carriers to share a small bandwidth without

interfering with each other. In the context of OFDM, these

individual carriers are often referred to as "sub-carriers".

In a data transmission system, a variety of mishaps

along the data transmission channel conspire to introduce IQ

imbalance errors into the signal as it makes its way from the

transmitter to the receiver. For example, as a result of

aging, temperature effects, or imperfections in their design,

the electronic components that carry out modulation at the

transmitter or demodulation at the receiver may fail to

generate two sinusoids that are perfectly matched in

amplitude and perfectly orthogonal in phase.

BRIEF DESCRIPTION OF THE FIGURES

FIG. 1 shows a data communication system;

FIG. 2 showsan equalizer;

FIG. 3 shows points in an IQ plane; and

FIG. 4 shows an adaptive filter.

DETAILED DESCRIPTION

The invention provides a method and system for

adaptively calibrating a receiver to correct for IQ imbalance

errors arising from direct conversion of a signal. As used

here, direct conversion refers to both direct up-conversion,

as performed by a transmitter, and direct down-conversion, as

performed by a receiver. Since the receiver calibration is

carried out without relying on information about the

transmitter, the receiver can correct IQ imbalance errors

with contributions from a variety of transmitters made by

different manufacturers.

FIG. 1 shows a data transmission system **10** having a

remote transmitter **12,** a transmission channel **14,** and a local

receiver **16**. Within the remote transmitter **12,** an IFFT block

18 generates a time-domain representation of an input signal

containing the symbols to be transmitted. The IFFT block **18**

provides this time-domain representation to an up-sampler **20,**

the output of which is filtered by a transmitter filter **22**.

The output of the transmitter filter **22** is then provided to a

multiplexer **24** that modulates each subcarrier with one of the

symbols to be transmitted. This multiplexer **24** introduces a

source of IQ imbalance error.

From the multiplexer **24,** the subcarriers radiate from a

transmitting antenna **26** and enter the transmission channel

14. Along the way, they encounter additional sources of

distortion. For example, reflections from obstacles can

result in multipath errors. In some cases, the frequencies of

the subcarriers may be shifted.

A receiving antenna **28** at the local receiver **16** captures

the subcarriers, together with any white noise in the

environment and any other interfering signals. This

hodgepodge of signals is then provided to a demultiplexer **30,**

which introduces another source of IQ imbalance error. The

output of the demultiplexer **30** is provided to an anti-alias

filter **32** and then to an inverse demultiplexer **34** whose

function is to remove any IQ imbalance introduced by the

demultiplexer **30**. The resulting signal is then provided to a

frequency-offset-correction block **36** to correct IQ imbalance

resulting from frequency offset errors that exist because of

any mismatches between the resonant frequency of an

oscillator at the local receiver and the corresponding

resonant frequency of an oscillator at the remote

transmitter.

The output of the frequency-offset-correction block is

then sampled by a down-sampler **38** and provided to an FFT

block **40**. The FFT block **40** provides a frequency-domain

representation of the signal to a channel-estimation-and-

correction block **42** that removes errors resulting from

multipath along the transmission channel **14**. This results in

a received signal that, except for any residual IQ imbalance

errors, is essentially identical to the input signal provided

to the remote transmitter **12**.

The received signal is provided to an equalizer **44**,

shown in more detail in FIG. 2. Within the equalizer **44** the

received signal is provided to a symbol-decision block **46**.

The symbol-decision block **46** then determines the

constellation point in the IQ plane that lies closest, in a

Euclidean sense, to the received point in the IQ plane.

FIG. 3 shows an exemplary IQ plane having constellation

points **48** distributed throughout four quadrants. These

constellation points **48** represent the possible symbols that
are understood by the data transmission system **10**. Also shown
in FIG. 3 is a received point **50** corresponding to the
received signal. As a result of IQ imbalance error, the
received point **50** does not coincide with any of the
constellation points **48**. Nevertheless, there does exist a
constellation point **52** that lies nearest to the received
point **50** in the IQ plane. This nearest constellation-point **52**
is defined by a two-dimensional constellation vector **c** having
components c_I and c_Q representative of in-phase and quadrature
components of the nearest constellation-point **52**. This
nearest constellation-point **52**, which is assumed to
correspond to the symbol that the received point **50** attempts
to communicate, forms the output of the symbol-decision block
46.

Referring back to FIG. 2, the received signal is also
provided to a multiplier **54**, which combines it with the
output of an adaptive-filter system **56**. The output of the
adaptive-filter system **56**, which can be represented as a 2x2
composite equalizing-matrix "W", is selected such that the
equalized signal provided at the output of the multiplier **54**
approximates the input to the remote transmitter **12**. The
reason the equalizing matrix is a "composite" equalizing-
matrix will be apparent from the discussion of FIG. 3.

6

A differencing element **58** receives the equalized signal and the nearest constellation-point **52** from the symbol-decision block **46**. The output of the differencing element **58** is an error signal indicative of the difference between these two quantities. This difference is characterized in FIG. 3 by a two-dimensional error vector ε, having components ε_I and ε_Q representative of in-phase and quadrature components, that characterizes the extent of the IQ imbalance. This error signal is then provided to a weight-update block **60**.

The weight-update block **60** then determines a new composite equalizing-matrix that, when used to generate another equalized signal, further reduces the magnitude of the error signal. The output of the weight-update block **60** is then provided back to the adaptive-filter system **56**, which then replaces its composite equalizing-matrix with a new composite equalizing-matrix as provided by the weight-update block **60**. This new composite equalizing-matrix is then used to generate a new equalized signal. The process continues until the magnitude of the error signal reaches a minimum or a pre-defined threshold. The error signal thus functions as a feedback signal for adjusting the composite equalizing-matrix on the basis of the extent to which the equalized signal differs from the nearest constellation-point **52**.

FIG. 4 shows in more detail the manner in which the

adaptive-filter system **56** uses both the positive and negative

frequency components of the received signal to generate the

composite equalizing-matrix. The adaptive-filter system **56**

includes a first adaptive filter **62** for generating a

positive-frequency equalizing-matrix from the positive

frequency components of the received signal and a second

adaptive filter **64** for generating a negative-frequency

equalizing-matrix from the negative-frequency components of

the received signal. The positive-frequency equalizing-matrix

and the negative-frequency equalizing-matrix are then

provided to a summer **66**, the output of which is the composite

equalizing-matrix.

Within the weight-update block **60**, the four weighting

coefficients that make up the composite equalizing-matrix are

updated by incrementing the previous weighting coefficients

by an amount proportional to the corresponding error signal

and to the received signal. The constant of proportionality

is selected to control the speed of convergence. A constant

chosen to ensure rapid convergence is apt to result in an

unstable system. Conversely, a constant chosen to ensure a

stable system is apt to converge slowly.

In some cases, the IQ imbalance error is so great that

the received signal does not correspond to the closest

constellation point in the IQ plane. Multipath in the

transmission channel can, in many cases, cause IQ imbalance

errors of this magnitude. In some embodiments, the local

receiver includes a channel-estimation-and-correction block

42 to correct these errors.

In the specialized case in which the data conforms to

the IEEE 802.11a standard, the method carried out by a

conventional channel-estimation-and-correction block **42**

interferes with the operation of the equalizer **44**. For

example, to correct for multipath errors, the 802.11a

standard provides a training signal that includes a pair of

training bits for each subcarrier. One of the pair of

training bits is associated with the positive frequency

component of that subcarrier; the other is associated with

the negative frequency component of that subcarrier. For half

of the subcarriers, these training bits have the same sign.

For the remaining half of the subcarriers, these training

bits have different signs.

To accommodate this disparate treatment of different

subcarriers in the training signal, the equalizer segregates

the subcarriers into two classes and processes them

separately. The first class includes those subcarriers for

which the corresponding training bits in the training signal

have the same sign. The second class includes those

subcarriers for which the corresponding training bits in the

training signal have different signs. IQ imbalance errors for

symbols carried by subcarriers in both the first and second

classes are corrected in the manner described above.

Segregating subcarriers into two classes in this manner

prevents the multipath correction performed on the first

class from interfering with convergence of an equalizing

matrix for subcarriers in the second class, and vice versa.

Other embodiments are within the scope of the following

claims: